

BEAT THE CLOCK COIL CHART

NOTICE:

THIS GAME OPERATES ON 24 VOLTS. WHEN ORDERING REPLACEMENT TRANSFORMERS, MOTORS, COILS OR METERS ---- MAKE SURE TO SPECIFY CORRECT PART NUMBERS.

NUMBER	DESCRIPTION	LOCATION
15 A 6771	TRANSFORMER - 60 CYCLE	MECH. PANEL
15 A 6773	TRANSFORMER - 50 CYCLE	MECH. PANEL
14 A 7746	SCORE MOTOR - 60 CYCLE	MECH. PANEL
14 A 7747	SCORE MOTOR - 50 CYCLE	MECH. PANEL
20 A 8757	24 VOLT METER	MECH. PANEL

SOLENOID COILS

A 23-600	REPLAY UNIT STEP UP	INSERT
A 23-650	MATCH UNIT STEP UP CLOCK UNIT STEP UP	INSERT INSERT
A 26-1350	BALL RELEASE COIL	BALL TROUGH
A 2-23-750	LARGE BELL KNOCKER COIL	INSERT CABINET
B 26-800	REPLAY UNIT RESET SCORE DRUM UNIT (3 REQ'D.)	INSERT INSERT
C 2-26-800	CHIME	INSERT
D 24-1400	BANK RESET COIL	PLAYFIELD
FL 21-375 / 28-400	FLIPPER COILS (2 REQ'D.)	PLAYFIELD
G 22-550	JET BUMPER COILS (5 REQ'D.)	PLAYFIELD
G 23-750	EJECT COILS (3 REQ'D.)	PLAYFIELD

RELAY COILS

M 29-1100	NO. 1 BUMPER RELAY NO. 2 BUMPER RELAY NO. 3 BUMPER RELAY 1 PT. RELAY 10 PT. RELAY 100 PT. RELAY SCORE RESET RELAY	PLAYFIELD PLAYFIELD PLAYFIELD INSERT INSERT INSERT INSERT
M 36-5500	25¢ RELAY	MECH. PANEL
Z 27-1000	RESET RELAY CLOCK RELAY EJECT RELAY TOP CENTER R.O. RELAY	MECH. PANEL MECH. PANEL MECH. PANEL MECH. PANEL
Z 28-1200	LOCK RELAY SET UP RELAY CHANGE RELAY	MECH. PANEL MECH. PANEL PLAYFIELD
Z 35-4200	COIN RELAY	MECH. PANEL

RELAY BANK COILS

X 27-500	RELAY BANK COIL	PLAYFIELD
X 27-700	RELAY BANK COILS (9 REQ'D.)	PLAYFIELD