



- WIRE COLOR CODE**
- VIRTUALLY OPEN GREEN WIRING WHEN ACTIVATED
 - VIRTUALLY CLOSED SWITCH POINT WHEN ACTIVATED
 - MAKE BEFORE BREAK
 - CIRCLE INDICATES POINT SWITCH ACTIVATED BY A MOTOR COIL WITH 25% OF COIL
- WIRE COLOR CODE**
- RED = RED
 - YELLOW = YELLOW
 - GREEN = GREEN
 - BLUE = BLUE
 - WHITE = WHITE
 - BLACK = BLACK
 - BROWN = BROWN
 - PINK = PINK
 - GRAY = GRAY
 - ORANGE = ORANGE
 - PURPLE = PURPLE
 - MAUVE = MAUVE
 - SLATE = SLATE
 - TEAL = TEAL
 - INDIGO = INDIGO
 - VIOLET = VIOLET
 - PURPLE = PURPLE
 - MAUVE = MAUVE
 - SLATE = SLATE
 - TEAL = TEAL
 - INDIGO = INDIGO
 - VIOLET = VIOLET
- EXAMPLE: W-1 INDICATES WHITE WIRE WITH A TRAIL AND ALSO A SECOND TIME.**

LEFT MOTOR 115V 1/2 HP 1725 RPM
 RIGHT MOTOR 115V 1/2 HP 1725 RPM
 TRANSFORMER 250V 0-270V 100VA
 TRANSFORMER 250V 0-270V 100VA

RELAY	SOLENOID	LAMP	SWITCH	OTHER
R-1	S-1	L-1	SW-1	
R-2	S-2	L-2	SW-2	
R-3	S-3	L-3	SW-3	
R-4	S-4	L-4	SW-4	
R-5	S-5	L-5	SW-5	
R-6	S-6	L-6	SW-6	
R-7	S-7	L-7	SW-7	
R-8	S-8	L-8	SW-8	
R-9	S-9	L-9	SW-9	
R-10	S-10	L-10	SW-10	
R-11	S-11	L-11	SW-11	
R-12	S-12	L-12	SW-12	
R-13	S-13	L-13	SW-13	
R-14	S-14	L-14	SW-14	
R-15	S-15	L-15	SW-15	
R-16	S-16	L-16	SW-16	
R-17	S-17	L-17	SW-17	
R-18	S-18	L-18	SW-18	
R-19	S-19	L-19	SW-19	
R-20	S-20	L-20	SW-20	