
COIN SWITCH ADJUSTMENT




.018" FOR 10¢ COIN

.032" FOR 5¢ COIN

.047" FOR 25¢ COIN

3 ADJUST THIS BLADE TO REST AGAINST BACKING BLADE WITH VERY LIGHT PRESSURE. 2 GRAMS MAXIMUM AT END OF BLADE.



1 ADJUST THIS BLADE AGAINST
WIRE FORM AS TIGHT AS
POSSIBLE WITHOUT RETARDING
PASSAGE OF COIN.
RECOMMEND:
5 TO 6 GRAMS FOR 10¢ COIN.
10 GRAMS FOR 5¢ COIN.
12 GRAMS FOR 25¢ COIN.

A-10233-1